

JUSTMENTS

GEOMETRY

ABL TH	(0, 3)	0
ABL MODE	(0, 3)	0
P ABL	(0, 15)	15
V SIZE	(0, 63)	35
V POSITION	(0, 63)	33
V COMP	(0, 3)	1
V LIN	(0, 15)	7
S CORRECTION	(0, 15)	7
H SIZE	(0, 63)	44
PIN AMP	(0, 63)	32
HCOMP	(0, 3)	0
UP CORNERPIN	(0, 63)	29
M PIN	(0, 3)	2
LO CORNERPIN	(0, 63)	29
TRAPEZIUM	(0, 15)	2
H POSITION	(0, 63)	40
AFC BOW	(0, 15)	8
AFC ANGLE	(0, 15)	9
LEFT BLK	(0, 63)	34
RIGHT BLK	(0, 63)	17
V ASPECT	(0, 63)	47
AKBTIM1	(0, 3)	2
AKBTIM2	(0, 1)	0
IKR		1
HNG		0
VNG		0

IF ADJUST

Automute	1
Audio Gain	0
L Gating	0

DAC

CONFIG		00000000
MPIN CONT	(0, 255)	96
HLIN	(0, 255)	83
HTRAP	(0, 255)	127
ROT. COIL	(0, 255)	130
PHOCUS PH	(0, 255)	90

SOUND

M-N	(0, 511)	200
M-D	(-128, -1)	-20
M-S	(+0, +127)	+20
S-M	(+0, +127)	+10
D-M	(-128, -1)	-10
N-M	(0, 1023)	496
BBE	(+0, +68)	+28
B1	(-96, +96)	+0
B2	(-96, +96)	+0
B3	(-96, +96)	+0
B4	(-96, +96)	+0
B5	(-96, +96)	+0
SW L	(-128, +0)	+0
SW F	(+5, +40)	+30
NICAM C AD		10001
NICAM Error	(0, 2047)	0
Stereo	(-128, +127)	+0

Status 0000000110

PANORAMA

RDPOSXM	(0, 511)	3
RDPOSYM	(0, 255)	10
BLANDEL	(0, 255)	0
BLANPOL	(0, 1)	0
BLANLEN	(0, 511)	0
YFRAMEM	(0, 15)	0
YBAGR	(0, 15)	0
HPANONM	(0, 1)	1
HSCPOSCM	(0, 4095)	2032
HSEG1HM	(0, 63)	3
HINCOM	(0, 511)	40
HSEG1LM	(0, 31)	0
HINC1M	(0, 511)	20
HSEG2HM	(0, 63)	6
HINC2M	(0, 511)	0
HSEG2LM	(0, 31)	0
HINC3M	(0, 511)	492
HSEG3HM	(0, 63)	9
HINC4M	(0, 511)	472
HSEG3LM	(0, 31)	0
HSEG4M	(0, 2047)	384
VPANONM	(0, 1)	1
VDOUBLEM	(0, 1)	0
VSCPOSCM	(0, 16383)	7619
VSEG1HM	(0, 31)	0
VINCOM	(0, 511)	0
VSEG1LM	(0, 31)	0
VINC1M	(0, 511)	0
VSEG2HM	(0, 31)	0
VINC2M	(0, 511)	0
VSEG2LM	(0, 31)	0
VINC3M	(0, 511)	0
VINC4M	(0, 511)	0
VSEG3M	(0, 1023)	0
VSEG4M	(0, 1023)	0
HORPOSM	(0, 2047)	0
HORWIDTHM	(0, 2047)	960
HORPOSG	(0, 2047)	29
HORWIDTHHG	(0, 2047)	0
HORFRAMEG	(0, 15)	3
PRIOP	(0, 7)	3
PRIOC	(0, 7)	5
PRIOS	(0, 7)	6
PRIOF	(0, 7)	7
PRIOM	(0, 7)	4
PRIOG	(0, 7)	1

SERVICE

SUB COL	(0, 63)	Adj
SUB HUE	(0, 63)	31
SUB SHARP	(0, 63)	30
SUB BRIGHT	(0, 63)	13
SUB CONT	(0, 15)	12
R-DRIVE	(0, 63)	50
G-DRIVE	(0, 63)	Adj
B-DRIVE	(0, 63)	Adj
R CUTOFF	(0, 63)	28
G CUTOFF	(0, 63)	24
B CUTOFF	(0, 63)	46
Br TXT	(0, 15)	7
Br OSD	(0, 15)	10